

EVENT RISK ASSESSMENT

Event:	Floe
Event Dates:	9th-11th December 2017 18.00-22.00
On-site Dates:	6th-12th December 2017
Site Address:	The Bridge Control Room, Hull
Risk Assessment date:	29th November 2017
Site visit by:	Paul Wigfield

CONTENTS:

- Page 2-3 Section 1: Introduction
- Page 4 Section 2: Electrical
- Page 5 Section 3: Projection Installation
- Page 6 Section 4: Installations in Public Areas
- Page 6 Section 5: Staff Manual Handling
- Page 7 Section 6: Working at Height Ladders
- Page 8 Section 7: Slips and Trips
- Page 9 Section 8: Fire Safety
- Page 10 Section 9: Vehicle Movements
- Page 10 Section 10: Further action required & additional notes



SECTION 1: INTRODUCTION

This is a site-specific risk assessment and method statement to supplement QED Productions Ltd's existing Health & Safety Policy.

QED Productions Ltd is supplying one low power Panasonic laser projector for external projection onto the west side of The Deep building.

This risk assessment identifies specific hazards and their risk ratings, control measures, and risk ratings after the control measures have been implemented.

QED Productions Ltd's management will ensure that staff are made aware of the significant findings of this risk assessment and the control measures necessary to eliminate or reduce the level or risk to the lowest possible level. A copy of this risk assessment should be available to all staff on site.

This Risk Assessment supplements any other risk assessments covering activities involving vehicle movements, structure construction and power generation.

Definitions

Hazard	The Hazard is something with the potential to cause harm, e.g. electricity, working at height, chemicals, vehicles
Risk	Combination of the likelihood and consequences of a specified hazardous event occurring.
Control Measures	The measures necessary to eliminate or reduce the level of risk
Risk Rating Without Controls	Level of risk before and control measures are implemented
Risk Rating With Controls	Level of risk after control measures have been implemented



SECTION 1: INTRODUCTION (Cont.)

Method used to determine the Risk Rating:

Likelihood (L)	The likelihood of harm occurring as a result of the hazard:								
	1 = Very unlikely								
	2 = Unlikely								
	3 = Possible								
	4 = Very likely								
	5 = Certain								
Potential Severity (S)	The potential severity of harm caused:								
	1 = Injury, no time off work								
	2 = Injury, time off work								
	3 = More than three days off work								
	4 = Long term absence								
	5 = Death								
Risk Rating (R)	Risk Rating = Likelihood (of the hazard occurring) X Potential Severity (of the loss):								
	Low = 7 or less								
	Med = 8 to 14								
	High = 15 or greater								



Hazard	Those at Risk		Rati	ng Controls	Control Measures	Risk Con	ng With	
1182810		L	S	R		L	S	R
Electrocution (240V and 415V)	Staff, other workers on site	3	5	High	 1 x 13amp power supply is being supplied for QED's usage and should be protected by a suitably rated RCD. System should be installed in agreement with IEE Regs (17th Edition) wherever practicable by a competent person All electrical equipment supplied by QED will have PAT certification Cables should be routed away from walkways and moveable items that could damage or break cables, e.g. furniture, etc. 	1	5	Low
Trips over cables	Staff, other workers on site	4	4	Med	• Staff will constantly monitor the site during the event	1	4	Low
Fire (electrical short circuits, overloads)	Staff, other workers on site	2	5	Med	 All electrical circuits should be protected by fuses or MCBs and RCDs Staff will constantly monitor the site during the event 	1	5	Low

QED Productions Ltd, Unit 11 Summit Road, Cranborne Industrial Estate, Potters Bar, Hertfordshire, EN6 3QW Tel: +44 (0)1707 648800 www.qed-productions.com Registered in England: 1983765



SECTION 3: PROJEC	TION INSTALLATIO	N							
Hazard T	Those at Risk	Risk F Contr		Without	Control Measures	Risk Rating With Controls			
		L	S	R		L	S	R	
Electrocution (240V and 415V)	Staff, other workers on site	3	5	High	See Section 2 - Electrical	1	5	Low	
Fire	Staff, other workers on site	1	5	Low	 Projector to be installed with reference to manufacturer's guidelines 	1	5	Low	
Working at height	Staff, other workers on site	N/A	N/A	N/A	 No working at height involved 	N/A	N/A	N/A	
Manual handing of AV equipment	Staff	4	3	Med	 all equipment to be handled in accordance with handling procedures as detailed in QED's manual handling policy Staff will have received manual handling training 	2	3	Low	

QED Productions Ltd, Unit 11 Summit Road, Cranborne Industrial Estate, Potters Bar, Hertfordshire, EN6 3QW Tel: +44 (0)1707 648800 www.qed-productions.com Registered in England: 1983765



SECTION 4: INSTALLATIONS IN PUBLIC AREAS											
Hazard	Those at Risk	Risk Rating Without Controls			Control Measures	Risk Con	ng With				
		L	S	R		L	S	R			
Personnel circulating in work areas	Staff	4	2	Med	 If any unauthorised persons are in the work area, installation should stop until the work area is clear Team working wherever possible to maximise vigilance for above processes 	1	2	Low			

Hazard Those at Risk		Ratii hout	ng Controls	Control Measures	Risk Rating With Controls			
		L	S	R		L	S	R
Manual handling (e.g. flight- cases, loudspeakers, projectors, etc.)	Staff	3	4	Med	 Equipment delivered as close as possible to area where used Team lifting as necessary Staff to be shown correct lifting techniques as appropriate Majority of equipment delivered in wheeled flight-cases 	1	4	Low



SECTION 6: WORKIN	G AT HEIGHT - LADD	DERS							
Hazard Those at Risk	Those at Risk		Rating out Cor	ntrols	Control Measures	Risk Rating With Controls			
		L	S	R		L	S	R	
Fall from Height	Staff	N/A	N/A	N/A	• QED is not intending to use ladders	N/A	N/A	N/A	
Objects falling from height	Staff, other workers on site, Public	N/A	N/A	N/A	 No working at height involved 	N/A	N/A	N/A	



Hazard	Those at Risk	Risk Rating Without Controls			Control Measures	Risk Rating Wi Controls		
		L	S	R		L	S	R
Spilt liquids	Staff, other workers on site	1	4	Low	 QED is not intending to use any liquids on site other than drinks Any spills to be cleaned up straight away Staff will constantly monitor the site during the event 	1	4	Low
Trips over cables	Staff, Other workers on site	4	4	Med	 Cables to be routed away from traffic routes wherever practicable Any cables over traffic routes should be flown, covered with suitable matting or approved vehicle-rated ramps Staff will constantly monitor the site during the event 	1	3	Low
Trips over floor-standing equipment	Staff, other workers on site	4	4		 Equipment to be sited away from traffic routes and within structures Equipment feet to be placed to minimise trip hazard Any equipment feet regarded as a potential trip hazard to be clearly marked with hazard tape 	1	4	Low



Hazard Those at Risk	Those at Risk	Risk Rating Without Controls			Control Measures	Risk Rating W Controls		
		L	S	R		L	S	R
Fire (localised)	Staff, other workers on site, general public	2	5	Med	 General fire fighting equipment is to be supplied by The Bridge Control Staff to monitor control areas and prevent the build up of any rubbish QED is not bringing any flammable liquids on to site All electrical circuits installed by QED to be protected by suitable RCDs 	1	4	Low
Fire (building / structures)	Staff, other workers on site, general public	2	5	Med	 The event organisers are in control of fire safety for staff and public The organiser is in control of site fire safety A copy of the organiser's fire safety plan should be made available to staff on site 	1	3	Low



SECTION 9: VEHICLE MOVEMENTS											
Hazard Those at Risk	Those at Risk		Rati hout	ng Controls	Control Measures	Risk Rating Wit Controls					
		L	S	R		L	S	R			
Collision with person, vehicle or object	Staff, other workers on site, general public	2	5	Med	 Vehicles only to operate as authorised by site staff Reversing with banksman if driver has restricted view Scheduling of vehicle movements for quiet times Comply with all venue vehicle regulations 	1	4	Low			

SECTION 10: FURTHER ACTION REQUIRED & ADDITIONAL NOTES

Fire Safety

A copy of the organiser's fire safety plan should be made available to QED staff on site